

LMP35UB/LMP60UB/LMP120UB/LMP250UB

Mini Digital Mixer Amplifier with USB FM & Bluetooth




- Rated power 35W/60W/120W/250W, speaker output: 70V/100V & 4-16Ω
- Built-in Class-D amplifier module, high efficiency (85%)
- With USB, FM and Bluetooth function
- Line 1-2 input of RCA interface and one RCA line output
- Mic 1 of 6.35mm in front panel with priority & muting
- Mic 2 of balanced XLR in rear panel with phantom power 48V
- Built-in EMC input for emergency use
- Priority level: EMC/Mic1 > AUX1/AUX2/Mic2
- Protection: Overload, Short circuit, Overheat, Clip
- Power supply: AC110V-240V/50Hz/60Hz & DC 24V
- LMP250UB power supply: AC110V-120V or AC220-240V & DC 24V



Phantom Power for Mic Input



DC 24V Power Supply



Built-in FM Module



Emergency Input with Gain Control



LMP35UB



LMP60UB



LMP120UB



LMP250UB

	RMS Power	Mic Sensitivity	Mic Freq.	AUX Sensitivity	AUX Freq.	Speaker Output	Dimension	Net Weight
LMP35UB	35W	8mV	180Hz-10kHz	360mV	70Hz-16kHz	70V/100V & 4-16Ω	250x200x66mm	2.5kg
LMP60UB	60W	8mV	180Hz-10kHz	360mV	70Hz-16kHz	70V/100V & 4-16Ω	250x200x66mm	2.6kg
LMP120UB	120W	10mV	180Hz-10kHz	360mV	70Hz-16kHz	70V/100V & 4-16Ω	250x200x66mm	3kg
LMP250UB	250W	10mV	180Hz-10kHz	360mV	70Hz-16kHz	70V/100V & 4-16Ω	250x230x66mm	3.7kg